



## CWLP Approved Meter Sockets

### Residential Service

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	AMPACITY	INSTALLATION TYPE	BYPASS	MANUFACTURER	CATALOG#	#OF TERMINALS	HUB SIZE	DIMENSIONS (WxHxD) (in)
3	1	125A	120/240	Residential	125A	Self-Contained OH Only	Lever	Millbank	U6193-RL-QG-AMS	5	1-1/4"	10"x18.5"x4.84"
3	1	125A	120/240	Residential	125A	Self-Contained OH Only	Lever	Millbank	U3505-DL-TG-HSP	5	2"	10"x18"x4.78"
3	1	200A	120/240	Residential	200A	Self-Contained UG/OH	Lever	Millbank	U9551-EL-TG-5T9	5	2-1/2"	13"x19"x 4.78"
3	1	200A	120/240	Residential	200A	Self-Contained UG/OH	Lever	Millbank	U9551-XL-TG	5	2-1/2"	13"x19"x4.875"
3	1	200A	120/240	Residential	200A	Self-Contained UG/OH	Lever	Eaton	UTTE5213BCH	5	2 1/2"	13.5"x20.5"x6"
3	1	200A	120/240	Residential	200A	Self-Contained UG/OH	Lever	Cutler-Hammer	UTH5213B	5	2-1/2"	13"x19"x5"
3	1	320A	120/240	Residential	320A	Self-Contained	Lever	Cutler-Hammer	UTH4330UCH	4	3-1/2"	36.6x15x5.7
3	1	100/125A	120/240	Residential	100/125A	Residential 2-Gang Horizontal	Lever	Landis & Gyr	UA4X11-ZG	4	2-1/2"	43.2x17.4x4.9
3	1	150A	120/240	Residential	150A		Lever	Millbank	U1234-X-HSP	4	2-1/2"	42.8x16x5.2
3	1	200A	120/240	Residential	200A		Lever	Millbank	U2734-XT--HSP	4	2-1/2"	42.2x25.25x6

### Commercial Service

WIRES	PHASE	SERVICE AMPS	VOLTS	SERVICE TYPE	AMPACITY	INSTALLATION TYPE	BYPASS	MANUFACTURER	CATALOG #	# OF TERMINALS	HUB SIZE	DIMENSIONS (WxHxD) (in)
3	1	200A	120/240	Commercial	200A	Self-Contained	Lever	Cutler-Hammer	UTTE4213UCH	4	4	19x13x5
4	3	200A	120/240	Commercial	200A	Self-Contained	Lever	Cutler-Hammer	UTH7213CCH	7	2.5	19x13x5
3	1	200A	120/240	Commercial	200A	Self-Contained	Lever	Milbank	U9551-RXL-QG	5	4	19x13x5
4	3	200A	120/240	Commercial	200A	Self-Contained	Lever	Milbank	U9701-RXL-QG	7	4	19x13x5
3	1	320A	120/240	Commercial	320A	Self-Contained Offset	Lever	Cutler-Hammer	UTH4338UCH	4	3.5	36.6x15x5.7
3	1	320A	120/240	Commercial	320A	Self-Contained Offset	Lever	Milbank	U5161-X-2/K2L	4		15x30x5
3	1	320A	120/240	Commercial	320A	Self-Contained Offset	Lever	Siemens	S48104-02	4	HD CL plate	31x16.2x5
3	1	320A	120/240	Commercial	320A	Self-Contained	Lever	Milbank	U1079-X-QG-K3-K2	4	4	38.75x13x5
4	3	320A	120/240	Commercial	320A	Self-Contained Offset	Lever	Cutler-Hammer	1008799CH	7	4	39.9x20x6.5
4	3	320A	120/240	Commercial	320A	Self-Contained	Lever	Milbank	U4911-X-QG-BL w/K4802 kit	7	4	38.75x17.75x6.5
4	3	320A	120/240	Commercial	320A	Self-Contained Offset	Lever	Milbank	U2594-X	7	4	17.75x34.125x6.5
4	3	320A	120/240	Commercial	320A	Self-Contained Offset	Lever	Milbank	U2120-X	7	4	17.75x31.75x6.5
4	3	200A	120/240	Commercial	200A	Self-Contained	Lever	Milbank	U2732-XT	7	2.5	25.25x32x5

**City Water, Light & Power, Electric Engineering, 1008 E. Miller St, Springfield, IL 62702, Ph 321-1350, Email [ElecEng.Rep@cwlp.com](mailto:ElecEng.Rep@cwlp.com)**